

ADVANCE

PARIS



X-A600

2x200W Power Amplifier

The X-A600 is the latest stereo power amplifier from Advance Paris.

The linear power supply is based on a 700VA toroidal transformer and a set of 6 capacitors for a total of 60000 μ F. In combination with the "very high current" power transistors (NJW0281G -NJW0302G), we guarantee a dynamic sound even under heavy loads.

The X-A600 delivers 200 Watts per channel in AB Class in 8 Ω . A "High BIAS" switch located at the back of the unit allows the X-A600 to deliver the first Watts in sliding A Class. Beyond this power, the switching to AB Class is done automatically.

The X-A600 has a very rigid chassis due to its mechanical design. Each circuit is separated from the others by a compartmentalized construction ensuring effective shielding.

The separate power amplifier is an indispensable part of any advanced audio system. Combined with the X-P700 preamplifier, you can build a high quality audiophile system that can delicately drive all speakers while exercising absolute control over the woofers.

Equipped with RCA and XLR jacks, the A-X600 can be used in High-Fidelity or Home-Cinema. For more discretion during your session, you have the possibility to turn off the VU-meters.



X-A600

2x200W Power Amplifier

SPECIFICATIONS

Power Output 8 Ω	2 X 200 W RMS
Power Output 4 Ω	2 X 300 W RMS
Frequency response	10 Hz – 80 kHz
Distorsion	Inf. to 0,007%
Signal to noise ratio	113 dB
Channel separation	108 dB
AC input	115V / 230V
Standby Consumption	Inf. to 0,5 W
Maximum consumption	575 W
Transformer power	700 VA
Transformer type	Toroidal
Inputs	LINE level on RCA and XLR
Input select (RCA / XLR)	Back panel switch
Outputs	Binding post : Banana / Spade / Bare cable
High-Bias setting	Yes
VU-Meter settings	Yes (ON / OFF / Low / Mid / Hi)
Remote control	No
Trigger	2 (IN / OUT) 12V
Product size (LxHxP in cm)	43,1x21x46,4
Packaging size (LxHxP in cm)	58,5x35,5x57,5
Gross weight (kg)	30
Net weight (kg)	25
Model N°	X-A600
EAN code	3760179292350