Stereo preamplifier

- The most advanced, single chassis solid state preamplifier we've ever made with an abundance of inputs to connect virtually any of your analog components and digital music sources.
- Supports many of the latest high resolution file formats including DSD files.
- Offers a secure, custom DSD connection for playback of SACDs when paired with the McIntosh MCT450 SACD/CD Transport.
- An 8 band analog equalizer lets you to fine tune your various music sources just the way you like.
- Headphone Crossfeed Director (HXD®) brings lifelike depth and spatiality to your music for your personal listening enjoyment.
- Home Theater Pass Through allows for seamless integration into your existing multi-channel home theater system.
- Classic styling permits the C52 to blend with new or old McIntosh systems and with any room decor.



















Stereo preamplifier

Frequency Response:

+0, -0.5dB from 20Hz to 20kHz +0, -3.0dB from 10Hz to 100kHz

Total Harmonic Distortion:

0.003% maximum from 20Hz to 20kHz

Signal to Noise Ratio (High Level): 100dB

Rated Output Voltage:

Balanced: 5 Vrms Unbalanced: 2.5 Vrms

Maximum Voltage Output:

Balanced: 16 Vrms Unbalanced: 8 Vrms

Digital Section:

3 optical and 2 coaxial inputs decode digital music at up to 24-bit/192kHz; 1 USB input accepts PCM signals up to 32-bit/384kHz and supports DSD64, DSD128 and DSD256 plus DXD 352.8kHz and DXD 384kHz

Overall Dimensions (W x H x D):

17-1/2" (44.45cm) x 7-5/8" (19.4cm) including feet x 18" (45.72cm) including the front panel, knobs and cables

Weight:

27.5 lbs (12.5kg) net,43 lbs (19.5kg) in shipping carton



For the Consumer's Protection:

In order to ensure the highest level of customer satisfaction, "new" McIntosh products may only be purchased over-the-counter or delivered and installed by an Authorized McIntosh Dealer. McIntosh products that are purchased over the Internet, by phone or mail order are presumed to be "used" and do not qualify for any McIntosh Warranty. McIntosh does not warrant, in any way, products that are purchased from anyone who is not an Authorized Dealer or products that have had their serial number altered or defaced.













Companion Products

The MC601 Amplifier, MCT450 SACD/CD Transport, MT5 Turntable, MR88 AM/FM/HD Tuner, MB100 Media Bridge, MEN220 Room Correction System, MPC1500 Power Controller and XR200 Loudspeakers are logical companions for the C52 Stereo Preamplifier. Your Authorized Dealer can provide additional information on other McIntosh product combinations.

To learn more, please call us at 1.800.538.6576.



www.mcintoshlabs.com